

# Sigrity 2022 軟體快速安裝手冊

1.	<u>軟硬體需求</u>
2.	安裝前準備與注意事項 ·······p.2
3.	<u>軟體來源</u>
4.	軟體授權伺服器端安裝與設定 ····································
5.	<u>用戶軟體安裝及 License</u> 連結設定····································
6.	<u>疑難排解</u> p.15

• Date: 2022/08/16	
• Author : Chen Yun	
· Revision: 1	
Version : Sigrity2022	
・備註:	





### 軟硬體需求

#### Windows

作業系統:

#### Sigrity2022 僅支援以下作業系統

- Windows 10 (64-bit)
- Windows 2016 Server (All service packs)
- Windows 2019 ServerWindows 10 (64-bit),

硬體規格:

- x86\_64 Compatible (includes P4 EMT and AMD Opteron<sup>™</sup>)
- 8 GB RAM
- Virtual memory at least twice physical memory 50 GB free disk space
- 1,024 x 768 display resolution with true color (16bit color)
- Broadband Internet connection for some service
- Ethernet card (for network communications and security hostID)
- Three-button Microsoft-compatible mouse

### 安裝前準備與注意事項

#### 軟體授權機制認證對象

- 軟體在使用時必須向授權伺服器取得使用授權,伺服器在啟動授權服務時必須核對授權License檔案的 內容與認證對象是否一致,如果License與網卡或硬體鎖號碼不一致,將無法啟動授權作業提供服務。
- 2. 授權對象為硬體設備,主要有以下兩種:
  - 2.1 網路卡的實體卡號 (MAC Address)。
  - 2.2 硬體鎖 (Dongle Key) · 如下圖所示



Note :

現階段僅提供 USB 硬體鎖服務,如果貴公司還在使用舊型 parallel port 型式的硬體鎖,請速向敝公司業務單位洽詢購買新式 USB 硬體鎖及 Re-Host 的服務。

#### Note :

- 在Windows server 不能以 Windows Remote Desktop (類似終端機) 的方式執行。
- 不支援Windows RT 及 Tablets。
- 電腦名稱不允許使用中文名稱或帶空格資料。
- 網路卡認證不支援虛擬環境。



#### 軟體進行安裝前使用者帳戶注意事項:

 請確認所登入的帳號擁有本機完整的 Administrator 管理者的操作權限(All user Mode) ·若是安裝 在Windows7 (或以上)作業系統中·請先將使用者帳戶控制設定(UAC) 調降至最低·避免安裝過程中 有太多的提示警訊而干擾安裝作業。



- 2. 請將已經安裝在作業系統中的防毒軟體及防火牆暫時關閉,以免影響程式的執行與設定。
- 3. 如果所購買的軟體版本的 License 的認證對象是 USB 硬體鎖,請勿先將 USB 硬體鎖插上你電腦上的 USB 插槽。因為作業系統內建的驅動程式版本較舊,使得硬體鎖無法順利安裝,你仍需要在稍後利用安 裝路徑下的新附帶驅動程式進行補安裝作業。





### 軟體來源

### Sigrity2022 若是"完整安装"需要安装以下套件:

- 1 OrCAD/Allegro 22.1 (SPB22.1)。(Sigrity 的 Aurora/Topology Explorer 及 Allegro 介面) 下載請至以下連結
  - 1.1 <u># Base\_SPB22.10.000 °</u>
- 2 Sigrity2022。(Sigrity 各項主程式及套裝如 PowerDC/SystemSI/Clarity/Celsius/...) 下載請至以下連結
  - 2.1 <u># Base\_SIG22.10.000</u>。

#### 取得方式

1. Cadence 官方網站下載專區進行 Sigrity2022 版本軟體的下載及安裝。

Operating Systems O IBMRISC		Enclose the search keyword within double quotes to look for an exact match. For example, "RHEL 8"			or an					
O LINUX Q Search 🚖									₽	
O SOLARIS My Preferred Releases										
WINDOWS	Click the release p	amo to vio	wall the available downloads in	cluding base unde	atos and b	otfixos				
○ SOLX8664	Click the release h		w all the available downloads in	iciduling base, upua	ates, anu n	ottixes.				
O OTHER	√↑ Release Name	Release	Release Version	√↑ Release Date	Supported	ported Operating System	Product List		List	
		Туре					Product #		Product Name	
Releases Filter by releases Q	SIGRITY/SYSANLS 2022.1	HOTFIX	Sigrity and Systems Analysis 2022.1 HF2 Release	05 Aug 2022	WINDOWS I WINDOWS	Windows 2016 Server; 10 (64B); WINDOWS	PA5700		Allegro Sigrity SI Base	
OAWR RF/Micro					2017 36176	1		Show More 💊	/	
OCADENCEHELP										
OFIDELITY POIN										1
OFIDELITY20221										
OFINEMARINE102										
OFINEOPEN111										
OFINETURB0161										
Note :										

■ 要執行 Sigrity 2022 你必須安裝最新的 Cadence License Manager 20.01 (FLEXnet License Manager version 11.17.1.0 或更新) · 並搭配新的 License 。



### 軟體授權伺服器端安裝與設定

#### **License Manager**

- 1 安裝
  - 1.1 解壓縮後,點選 setup.exe。

¦硜磲(C:) > Cadence > 2019

密磲(	C:) > Cadence > 2019				✓ C
名種	م ب	修改日期	類型	大小	
	AutoPlay	2019/10/22 下午 05:40	檔案資料夾		
	Disk1	2019/10/23 下午 01:06	檔案資料夾		
	Disk2	2019/10/22 下午 05:38	檔案資料夾		
	Disk3	2019/10/22 下午 05:39	檔案資料夾		
	LibCD	2019/10/16 下午 03:22	檔案資料夾		
13	autorun.inf	2014/9/19 下午 03:56	安裝資訊	1 KB	
ZIP	Base_SIG3DEM19.00.000_wint_1of1.zip	2019/12/9 上午 11:11	壓縮 (ZIP) 檔案	2,233,309	
ZIP	Base_SIG19.00.000_wint_1of3.zip	2019/11/4 下午 04:17	壓縮 (ZIP) 檔案	4,200,076	
ZIP	Base_SIG19.00.000_wint_2of3.zip	2019/11/4 下午 04:19	壓縮 (ZIP) 檔案	4,095,415	
ZIP	Base_SIG19.00.000_wint_3of3.zip	2019/11/4 下午 04:17	壓縮 (ZIP) 檔案	3,433,304	
	DownloadManager_SIG19.00.000_win	2019/12/10 上午 09.48	應用程式	58,236 KB	
0	setup.exe	2014/9/19 下午 03:56	應用程式	2,558 KB	
P	setup.exe.config	2019/9/27 T+ 12.20	CONFIG 檔案	1 KB	
13	setup.ini	2019/8/29 上午 08:28	組態設定	1 KB	

#### 1.2 點選 License Manager。



# cādence°

 $\odot \propto$ 

Installs the Cadence License Manager. Install the License Manager first to ensure the latest version.





#### 1.3 確認 License Manager 為 20.01 版後,點選 Next。



**1.4** 閱讀完軟體合約,選擇 I accept the terms of the license agreement 後,點選 Next。如果不同意 則無法進入下一個步驟。

Cadence License Manager 20.01-s002 - InstallShield Wizard					
License Agreement Please read the following license agreement carefully.	nce®				
CADENCE DESIGN SYSTEMS, INC. SOFTWARE LICENSE AND MAINTENANCE AGREEMENT	^				
THIS SOFTWARE LICENSE AND MAINTENANCE AGREEMENT ("AGREEMENT") IS A LEGAL DOCUMENT BETWEEN YOU AND CADENCE DESIGN SYSTEMS, INC. ("CADENCE"). PLEASE READ THIS AGREEMENT CAREFULLY BEFORE INSTALLING Y CADENCE SOFTWARE ("SOFTWARE"). BY USING THE SOFTWARE, YOU (EITHER J INDIVIDUAL OR A BUSINESS ENTITY) AGREE TO BE BOUND BY THE TERMS OF TH AGREEMENT. IF YOU DO NOT WANT TO BE BOUND BY THE TERMS OF THIS AGREEMENT, CADENCE IS UNWILLING TO LICENSE THE SOFTWARE TO YOU, IN WHICH EVENT YOU MUST PROMPTLY RETURN THE SOFTWARE AND ALL ACCOMPANYING ITEMS (INCLUDING MANUALS, BINDERS OR OTHER CONTAINERS	YOUR AN HIS				
I accept the terms of the license agreement	Print				
$\bigcirc$ I <u>d</u> o not accept the terms of the license agreement					
InstallShield < <u>B</u> ack <u>N</u> ext >	Cancel				



#### 1.5 選擇安裝路徑後,點選 Next。

Cadence Li	cense Manager 20.01-s002 - I	nstallShield W	izard	×
Choose D Select fo	estination Location Ider where setup will install files.		cād	ence <sup>®</sup>
	Install Cadence License Manager 2 C:\Cadence\LicenseManager	0.01-s002 to:		<u>C</u> hange
InstallShield -		< <u>B</u> ack	<u>N</u> ext >	Cancel

#### 1.6 確認安裝項目為 Licensing 後,點選 Next。





#### 1.7 確認上述步驟無誤後,點選 Install。

🚜 Cadence License Server Configuration - Version 1.0.11.0

-			 -	
1 1	Conco	- H 1		101
L	ICCHSC	T. TI	LUCAI	IOI



 $\times$ 

 Specify the location of the license file that you had received from Cadence, then click Next.

 License File

 Browse...

 Help

 Next >
 Cancel

#### 1.8 指定所要使用的軟體授權檔案(License File)後,點選 Next。

Cadence License Manager 20.01-s002 - InstallS	hield Wizard X
Ready to Install the Program	cādon co <sup>®</sup>
The wizard is ready to begin installation.	cauence
Click Install to begin the installation.	
If you want to review or change any of your installati exit the wizard.	on settings, click Back. Click Cancel to
InstallShield	
< E	ack Install Cancel

- 1.9 設定 License Server 所需相關環境,系統會主動套用主機名稱及設定 License Server 所使用的 通訊埠及主機名稱等相關訊息後,點選 Next。
- Port Number → Cadence 軟體產品內定皆為使用 5280 通訊埠
- Host Name → 主機名 (請注意不能有中文或空格·否則建議改用你的固定 IP·如 192.168.1.199)
- Log File → License Manager 的訊息檔名內定為 debug.log
- Options File → 外掛宣告檔(一般不用設定)



■ Vender Daemon Port Number → 指定另一個 Port Number(一般不用設定)

🚜 Cadence License Server Configuration					
License Server Data <b>cādence</b>					
Specify the license - License Server	server information in th	e fields below, th	nen click Next.		
Port Number:	Host Name:	Host ID	t:		
5280	Chenyun-T430s	843A4	4B306A7C		
Log File: C:\Cade	ence\LicenseManager'	\debug.log	Browse		
Options File:			Browse		
Vendor Daemon	Port Number: 3000				
Help	< Back	Next >	Cancel		

1.10 安裝成功,出現 successfully 等字眼後,點選 Finish。

🚜 Cadence License Server Configuration	×
Configuration Status cād	ence
- Cadence License Server started successfully with the new license file 'C:\Cade \LicenseManager\license.dat'.	nce 🔨
- The new license server setting '5280@Chenyun-T430s' was successfully dde CDS_LIC_FILE license path environment variable.	d to your
	~
Click Finish to exit the Cadence License Server Configuration utility.	Finish

Note :

■ 如果出現 Fail 畫面 · 須用手動方式設定 License · 請參考疑難排解 → <u>人工設定 License Server 操作</u> 步驟 。



## 用戶軟體安裝及 License 連結設定

#### **Product Installation**

Note :

- 建議你將防毒軟體關閉,讓程式可以順利安裝。
- 1 安裝。
  - 解壓縮後,點選 setup.exe。 1.1

碟 (C:) > Cadence > 2019

嘧磲(C:) > Cadence > 2019				✓ Ŭ
名稱 ^	修改日期	類型	大小	
AutoPlay	2019/10/22 下午 05:40	檔案資料夾		
Disk1	2019/10/23 下午 01:06	檔案資料夾		
Disk2	2019/10/22 下午 05:38	檔案資料夾		
Disk3	2019/10/22 下午 05:39	檔案資料夾		
LibCD	2019/10/16 下午 03:22	檔案資料夾		
📓 autorun.inf	2014/9/19 下午 03:56	安裝資訊	1 KB	
Base_SIG3DEM19.00.000_wint_1of1.zip	2019/12/9 上午 11:11	壓縮 (ZIP) 檔案	2,233,309	
Base_SIG19.00.000_wint_1of3.zip	2019/11/4 下午 04:17	壓縮 (ZIP) 檔案	4,200,076	
Base_SIG19.00.000_wint_2of3.zip	2019/11/4 下午 04:19	壓縮 (ZIP) 檔案	4,095,415	
Base_SIG19.00.000_wint_3of3.zip	2019/11/4 下午 04:17	壓縮 (ZIP) 檔案	3,433,304	
DownloadManager_31619.00.000_win	2019/12/10 上午 09.40	應用:20	58,236 KB	
0 setup.exe	2014/9/19 下午 03:56	應用程式	2,558 KB	
setup.exe.config	2019/9/27 T-+ 12.20	<del>CONHO 備案</del>	1 KB	
🗟 setup.ini	2019/8/29 上午 08:28	組態設定	1 KB	

#### 1.2 點選 Product Installation。





#### 1.3 確認版本為 Sigrity2022 版後·點選 Next。



**1.4** 閱讀完軟體合約,選擇 I accept the terms of the license agreement 後,點選 Next。如果不同意 則無法進入下一個步驟。

Cadence Systems Analysis Sigrity 2022.1		$\times$				
License Agreement						
Please read the following license agreement carefully.	adenc	e				
CADENCE DESIGN SYSTEMS, INC. SOFTWARE LICENSE AND MAINTENANC AGREEMENT	E	^				
THIS SOFTWARE LICENSE AND MAINTENANCE AGREEMENT ("AGREEMENT"	") IS A	1.1				
("CADENCE"). PLEASE READ THIS AGREEMENT CAREFULLY BEFORE INSTAL	LING YOUR					
CADENCE SOFTWARE ("SOFTWARE"). BY USING THE SOFTWARE, YOU (EI INDIVIDUAL OR A BUSINESS ENTITY) AGREE TO BE BOUND BY THE TERMS	OF THIS					
AGREEMENT. IF YOU DO NOT WANT TO BE BOUND BY THE TERMS OF THIS	S LL TN					
WHICH EVENT YOU MUST PROMPTLY RETURN THE SOFTWARE AND ALL	0, 11					
ACCOMPANYING ITEMS (INCLUDING MANUALS, BINDERS OR OTHER CONTA AND ANY OTHER PRINTED MATERIALS) WITHIN 30 DAYS. BY CLICKING YES	AINERS, DURING	~				
	TENANCE					
• <u>Laccept the terms of the license agreement</u>	Print					
$\bigcirc$ I <u>d</u> o not accept the terms of the license agreement						
InstallShield						
< Rack Next >	Cance	1				
	Cance	•				



### 1.5 選擇 Complete · 點選 Next。

Cadence System	s Analysis Sigrity 2022.1	×
Setup Type Select the setu	p type that best suits your needs.	cādence
Please select	a setup type.	
© <u>Complete</u>	All program features will be installed. (Requires the most disk space Space Required: 17.41 GB	a.)
◯ Cu <u>s</u> tom		
÷.	Select which program features you want installed. Recommended fo users.	or advanced
InstallShield ——		
	< <u>B</u> ack <u>N</u> ext>	Cancel

若你是勾選 Custom · 請透過 Bowser 鍵來選擇安裝項目控制檔 Control file · 需要有 Control\_xxxxxxx.TXT 的檔案。

1.6 選擇要安裝的路徑與要連接的 License Server。(如果要連接兩台以上的 server · 需用分號隔開 )

Cadence Sys	tems Analysis Sigrity 2022.1	X
Choose Do Select fol	estination Location der where setup will install files.	cādence <sup>°</sup>
	Install Cadence Systems Analysis Sigrity 2022.1 to: C.\Cadence\Sigrity2022.1	<u>C</u> hange
	Space Required: 17.41 GB	Space Available: 46.95 GB
License	Path	
	5280@Chenyun-B9400ce	
InstallShield –		
	< <u>B</u> ack	. <u>N</u> ext > Cancel



1.7	確認要安裝的軟體後,	點選 Install。

Installation Summary	×
Start Copying Files Review settings before copying files.	cādence
Setup has enough information to start copying the program files change any settings, click Back. If you are satisfied with the set copying files.	s. If you want to review or ttings, click Next to begin
Current Settings:	
- Products to install: Allegro Sigrity Package Analysis Allegro Sigrity Power Aware SI Allegro Sigrity Power Integrity Signoff Allegro Sigrity System Serial Link Option Sigrity Aurora Cadence IO-SSO Analysis Suite Celsius	
Clarity	>
InstallShield	
< <u>B</u> ack	Install Cancel

### 1.8 安裝完成後·點選 Finish 即可。

Cadence Systems Analysis Sigri	ity 2022.1
	InstallShield Wizard Complete
	The wizard was interrupted before Cadence Systems Analysis Sigrity 2022.1 could be completely installed. Your system has not been modified. To install this program at a later time, please run the setun again.
	Click Finish to exit the Setup wizard.
	< <u>B</u> ack <b>Finish</b> Cancel



存 Cadence Sigrity Suite Mana	er	_		×
SN2SPD	Suite	Version	Platform	FileNa 🔺
GDS2SPD	Sigrity Advanced PI	22.1.2.07291	x64	C:\Cad
NDD2SPD	Sigrity Package Assessment and Model Extraction Suite	22.1.2.07291	x64	C:\Cad
OASIS2SPD	Sigrity Enterprise	22.1.2.07291	x64	C:\Cad
PADS2SPD	Sigrity Power Integrity Suite	22.1.2.07291	x64	C:\Cad
🐝 RIF2SPD	PowerDC II	22.1.2.07291	x64	C:\Cad
🍓 SPDLinks	IC Package Extraction Suite	22.1.2.07291	x64	C:\Cad
TS AMM	Clarity Advanced IC Package Extraction Suite	22.1.2.07291	x64	C:\Cad
STORAGE SPICE	Celsius DC	22.1.2.07291	x64	C:\Cad
👽 Celsius	Clarity IC Package Extraction Suite	22.1.2.07291	x64	C:\Cad
👽 Celsius2D	Sigrity PKG-PCB SSO Voltus suite	22.1.2.07291	x64	C:\Cad
🐨 Celsius3D	Advanced IC Package Extraction Suite	22.1.2.07291	x64	C:\Cad
CelsiusCFD	PowerDC	22.1.2.07291	хб4	C:\Cad
Clarity 3D Transient Solver	Celsius 2D Electrothermal Solver	22.1.2.07291	x64	C:\Cad
30 Clarity3DLayout	Allegro Sigrity Power Integrity Signoff and Optimization Option (HS)	22.1.2.07291	x64	C:\Cad
30 Clarity3DWorkbench	Sigrity StarterPack	22.1.2.07291	x64	C:\Cad
S LavoutWorkbench	Celsius Advanced PTI	22.1.2.07291	x64	C:\Cad
OntimizePI	Signity Advanced PI II	22.1.2.0/291	x64	C:\Cad
PowerDC				
PowerSI	Information for Tools and License			
PowerTree	Enumerating Cadence products. Please wait			
SigritySuite	License initialization			
Speed2000 Generator	Eetching suite license information			
Speed2000 Simulator	Einished fetching product license information. Data is ready			
SpeedEM Generator	Thisted retening product itemse information, but is ready.			
SpeedEM Simulator				
W System Explorer				
SystemSI				
2 <sub>B</sub> T2B				
S XcitePI				
XtractIM				•
	Who is us	ing License Se	rver	Exit

#### 2 解除安裝

Graser

如果想要卸載任何程式,可以依照以下步驟操作。

- 2.1 在以下路徑找到要解除安裝的程式。
- 2.2 點選右鍵解除安裝即可。

~	截定		
ŵ	首百	應用程式與功能	
-	i我設定	AWR Design Environment 16 (16.01.12506	i.1) 64-bit 2.59 GB 2022/2/18
		Bandizip	2021/4/7
15	應用程式與功能 預設應用程式	Cadence Download Manager	2021/9/15
U <u>1</u>	雜線地震	Cadence License Manager 20.01-s002 20.01.0002	2022/8/23
	以應用程式開啟網站 影片播放	187	收 解除安装
Ŧ	RD	Cadence OrCAD and Allegro (Incl ADW)	17.2 2021/4/12
		Cadence OrCAD and Allegro 17.4-2019	2022/6/1
		Cadence Sigrity 2019	2021/4/12
		Cadence Systems Analysis Sigrity 2021.1	2022/5/9
		Cadence Systems Analysis Sigrity 2022.1	2022/8/23
		CCleaner	2021/4/7
		Gisco Webex Meetings	297 MB



#### Note :

■ 要執行 Sigrity 2022 你必須安裝最新的 Cadence License Manager 20.01 (FLEXnet License Manager version 11.17.1.0 或更新), 並搭配新的 License。因此需先卸載舊版的 License Manager。

### 疑難排解

如遭遇無法正常啟用 License 的情況,請執行下列步驟嘗試排除問題:

1 關閉防毒軟體及防火牆。

		-	×
← → ◇ ↑ 🔐 > 控制台 > 所有控制台項目 > Windows Defender 防火進 > 自訂設定 🗸 🗸	搜尋控制台		Q
自訂每個網路類型的設定 您可以為您使用的每個網路類型修改防火機設定。 網域網路設定			
□ 封鎖所有違人速爆,包括來自允許的應用程式遵單中之應用程式的連入連線 ☑ 當 Windows Defender 防火牆封鎖新的應用程式時語通知我			
<ul> <li>         ·</li></ul>			
<ul> <li>國戰 Windows Defender 防決選</li> <li>封銀所有進入連線。包括來自公許的應用程式達單中之應用程式的通入連線</li> <li>図 當 Windows Defender 防決: &gt;</li></ul>			
● 關閉 Windows Defender 防火牆 (不連議) 公用網路設定			
<ul> <li>Q 關啟 Windows Defender 防火牆</li> <li>對鎖所有連入連線,包括來自允許的應用程式適單中之應用程式的連入連線</li> <li>② 當 Windows Defender 防火繼封鎖新的應用程式時聽通知我</li> </ul>			
● 關閉 Windows Defender 防火進 (不建議)			

2 確認 client 端與 License server 之間的連線是否暢通。 在 Windows 的執行窗輸入 CMD 指令 以開啟 DOS 視窗,並輸入 ping License server 電腦名稱。





3 確認使用者電腦環境變數中 CDS\_LIC\_FILE 的設定是否正確對應到 5280@License Server 電腦名稱。

License Server 可以有多個存在,中間需用分號隔開,License 會先去抓取較前面的 Server,如抓 取不成功,再依序抓取後面的 Server。

Ex :

#### 設定 5280@Chenyun-T430s;5280@spbserver

會先抓取 Chenyun-T430s 這台的 Server License,如未抓取成功,程式會再抓取 5280@spbserver 這台的 Server License。

← → ~ ↑	☑ > 控制台 > 系統及安全性 > 系統	環境變數		×
控制台首頁	系統內容 ×	- chenyun 的使用者變	數(U)	
<ul> <li>● 從置當環員</li> <li>● 邊周設定</li> <li>● 糸底伝羅</li> <li>1</li> <li>● 増増糸抗設定</li> </ul>	<ul> <li>電腦名稱 硬體 增陽 未成保護 道端 您必須以未統管理員的身分登入,才能要更這裡的大部分設定。 交配 視覺效果、虛場器排程、記像體使用量和虛擬記個體</li> <li>股定(5)</li> <li>使用者設定備 關於您登入時的貞面設定</li> <li>股定(5)</li> <li>転動及修復</li> <li>未成款動、未成失敗、及僕講宴訊</li> <li>股定(7)</li> <li>2 環境室(7)</li> </ul>	要教 (CDS_LIC_FILE CDS_LIC_ONLY OneOrive Path 条統理教(S) 選教 (CDS_LIC_FILE CDS_LIC_FILE CDS_LIC_FILE CDS_LIC_FILE CDS_LIC_FILE DriverData	<ul> <li>              金             </li> </ul> <li>             S280@Chenyun-T430s;5280@spbserver         <ul> <li>C\User\chenyun-GRASER\AppData\Loc,</li> <li></li></ul></li>	3
請參閱 安全性與維護	確定 取済 書用(A)			

4 請確認所登入的 User 帳號擁有本機完整的 Administrator 管理者的操作權限,並且確認對C:\Cadence 資料夾擁有完整的控制權限。

名稿	修改日期 類型	■ Cadence - 内吾 3 × □ Cadence 的權限	×
Allegro Basic Lab	2019/11/15 下午 檔案資料	7 一般 共用 安全性 以前的版本 自訂 安全性	
1 Cadence inetpub Intel PerfLogs Program Files SPB_Data	<ul> <li>開散(O)</li> <li>在新視塞開散(E)</li> <li>幻道到[快速存取]</li> <li>聖編為「Cadence.zip」</li> <li>堅編為「Cadence.7z」(7)</li> <li>新増至氫編構 (Bandizip)(B)</li> </ul>	初件名稱:     C:\Cadence       都培名稱:     C:\Cadence       難組或使用者名稱(G):     難組或使用者名稱(G):       離 Authenticated Users     離 Authenticated Users       離 SYSTEM     龜 Authenticated Users       龜 Authenticated Users     龜 SYSTEM       龜 Authenticated Users     龜 SYSTEM       龜 Authenticated Users     龜 SYSTEM       龜 Administrators (CHENYUN-T430S\Administrators)     龜 Users (CHENYUN-T430S\Users)	
<mark>。</mark> Windows <mark>。</mark> 使用者	接興存取權給(G) > 邊原裔版(V) ● 使用 ESET Endpoint Antivirus 掃描	<sup>5</sup> 若要學更確限,請按一下[編輯]・ Users 的權限(P) 允許 拒絕 新増(D) 移除(R)	
	進階編項         >           加入至煤體徑(1)         >           釘攝到開始畫面(P)	停衣 ✓ ▲ ▲ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓	•
	(明送到(N) → 朝下(T) 複製(C)		
	建立禮徑(S) 刪除(D) 重新命名(M)	確定 取満 変用(A	
2	內容(R)		



Graser

5.1 當無法使用 LicenseServerConfiguration 程式設定順利成功時,請先用文書處理器 (例如記事本,Wordpad...) 打開有 License 字樣的檔案,內容類似如下:

請先確認以下紅框處與你的序號資料有相符

5.1.1 網卡認證:網卡序號。

5.1.2 USB 認證: USB 上的序號。

→ × T <u></u> → 本信	₹> - 41就18	et∉ (C:) > Cadence >		+7 21	-t-ds
快速存取		合傳	11151 CX 口 州	明尘	入小
百兩		<mark>  </mark> 17.4	2019/12/10 上午	檔案資料夾	
来四 D		2018	2019/12/9 下午 0	檔案資料夾	
1 又件	A	2019	2019/12/10 上午	檔案資料夾	
☴ 圖片	*	🚽 DownloadManager	2019/12/10 上午	檔案資料夾	
ChenYun	*	LicenseManager	2019/12/11 下午	檔案資料夾	
ChenYun	*	Sigrity2018	2019/12/10 上午	檔案資料夾	
install		Sigrity2019	2019/12/11 上午	檔案資料夾	
LicenseManager		E Hotfix_SIG18.00.004_wint_1of1 .exe	2019/12/9 上午 1	應用程式	2,890,573 KE
- Licenseivianager		Hotfin SDP17 20.062 mint 1 of1 ovo	2010/12/0 上午 1	降田的社	2,059,200,40
PowerDC		License_89039_FLEXID=9-485C48B2_4	2019/7/2 下午 04	文字文件	120 KE
PowerDC					

5.2 將 Cadence\_SERVER 字串欄位部分,修改成你的 License Server 主機名稱 (ex:我電腦名稱 為 Chenyun-T430s)

5.3 修改好後·將檔案另存新檔·並把檔名命名為 license.dat·然後複製到 LicenseManager 安裝路徑下·將舊的 License File 予以取代。

#### ★ 快速存取 重 桌面 量 文件 ■ 国月 \* 9 \* flexid doc bz2.pvd hashlib.pvd Izma.pvc ssl.pvd ctupes pud ChenYun \* Cadence install PowerDC PowerDC cādence cdslmd.exe CKOUT.exe altosda.exe ambitd.exe sd ex alta.exe Cadence\_Logo Red\_Reg.gif OneDrive installs.exe 💷 本機 二 主機 3 D 約年 予 数 ○ 文件 ♪ 数果 二 点型 二 工物証確(C) 二 工物証確(C) 二 工物証確(C) W FeatureValic exe g2c\_d.exe haspsrm\_win32. dll hlds.exe InstLog1211201 9\_180355.txt k2techld.exe AG-UTILITY EADME.rtf haspsrm\_win64. dll 易 昺 00 0, 0 mfc80.dll LicenseClientCo nfiguration.exe Lic nseFileValidi ty.exe LicenseServerCo nfiguration.exe LicenseServerDi agnostics.exe ImCheckExpirat on.exe Imgrd.exe Iminstall.exe Imutil.exe \$ 🥔 網路

#### 5.4 開啟 Lmtools.exe。

Graser

#### 5.5 確認相關檔案設定後,點選 Save Service。

LMTOOLS by Flexera Software LLC	_		×
File Edit Mode Help			
Service/License File   System Settings   Utilities   Start/Stop/Reread   Server Status   Server Diags	fig Services	Borrowing	
Configure Service 2	Save Se	ervice	
Service Name Cadence License Manager	Remove S	Service	
Path to the Imgrd.exe file C:\Cadence\LicenseManager\Imgrd.exe Browse			
Path to the license file C:\Cadence\LicenseManager\license.dat Browse			
Path to the debug log file C:\Cadence\LicenseManager\debug.log Browse Vie	ew Log	Close Log	)
I Start Server at Power Up I Use Services I FlexNet Licensing Start Server at Power Up I Services I flex Net Licensing Services into the FlexNet Licensing Services into the service with the service withe service with the service with the servi	ervice Requ Service is rec	iired quired for op	tional
reatures such as virtuaiz	ation and th	usted storag	e.



5.6 重新執行 License。

5.6.1 點選 STOP Server,停止原先的 License 服務。

- 5.6.2 點選 ReRead License File, 讀取 License 檔案內容。
- 5.6.3 點選 StartServer ,執行 License。
- 5.6.4 確認 Server Start Successful 。

LMTOOLS by Flexera Software LLC	_		×
File Edit Mode Help			
Service/License File   System Settings   Utilities Start/Stop/Reread Server Status   Server Diags   Config	Services	Borrowing	Ι.
FlexNet license services installed on this computer Cadonos Ucense Manager Log			
3			
Start Server Stop Server ReRead Lice	nse File		
Edit Advanced settings NOTE: This box must be checked to shut down a li when licenses are borrowed.	cense serve	er	
4			
Server Start Successful.			

# Graser®

本版 Technic Note 版權為 映陽科技股份有限公司 所有,未經允許不得任意轉用。 © 2022 Graser Technology Co.,Ltd.